



The new GSL Battery Chargers are revolutionary 4 Stage charger conditioners, utilising Switchmode and microprocessor technology and designed to charge 12 and 24 Volt Lead Acid and Calcium Batteries. As a Lead Acid and Calcium Battery Charger, the unit provides a safe and fast method of restoring discharged batteries and maintaining them, via precisely controlled Bulk, Absorption, Float and Pulse stages.

The chargers feature a high operating efficiency of above 80% and virtually no power consumption during standby without a battery connected. The chargers are fully protected against overload, short circuit, over temperature, reverse polarity connection, over voltage and with a bulk charge timeout for additional safety. The chargers are built in a compact and strong aluminium extrusion which can be easily secured to both vertical and horizontal surfaces and will be fully operational with voltages as low as 190Vac or as high as 260Vac.

Before starting the charge cycle the battery voltages are evaluated to detect faulty batteries.

BULK MODE – This mode of the battery charger delivers bulk charging current regulated to 10/18/20/30 Amps into the battery being charged. When the battery voltage rises to approximately 14.3V/15.3V/ 28.6V/30.6V and the battery is 70% recharged. The charger will switch automatically to Absorption Mode.

ASORPTION MODE – In this mode the battery charger output voltage is maintained at 14.3V /15.3V/ 28.6V/30.6V until the current drops below a controlled threshold. The battery is brought up to a 90% recharge.

FLOAT MODE - The voltage is reduced to 13.5V/14V/27V/28V and maintained at that level with the charger supplying just enough current to maintain the battery at full capacity.

PULSE MODE – Periodic low current pulse to maintain maximum battery life.

Installation & Safety Precautions:

- a. This appliance is not meant for use by young children or infirm persons without supervision.
- b. During charging process, do not use a naked flame near a battery, due to gases emitted from the battery, which may ignite and explode.
- c. Never smoke or light cigarettes near a battery.
- d. Do not place tools on top of battery or allow tools to fall on battery.
- e. Always wear eye protection near a charging battery.
- f. Ensure a “well” ventilated area is used when testing or re-charging batteries.
- g. Ensure ventilation is adequate and venting holes are not obstructed. Inadequate ventilation may over-heat the unit and cause inefficient operation.
- h. The battery charger is intended for indoor use only. Do not expose it to extreme weather conditions e.g. rain or dampness.
- i. If skin or clothing comes into contact with acid, flush the area(s) with water immediately. Seek medical attention if necessary.
- j. The battery charger contains hazardous voltages. There are no user serviceable components inside. If the AC supply cord is damaged, in order to avoid a hazard it must be replaced by the manufacturer or its service agent or a similarly qualified person.

Should product require service, return it to place of purchase for warranty advice.

Battery Charging Times:

The question of “how long will my battery take to re-charge?” is always asked. Firstly, the charge rate (CR) of a battery is rated in Amps and the battery capacity (C) in Amp Hours. The battery manufacturer for each battery type normally states this CR. As a rule of thumb, a lead acid battery generally should be charged under approximately 1/5 of C.

For example: if you have a 100Ah battery, the recommended charging current is: $100 / 5 = 20A$.

The majority of the battery capacity would normally be charged in 5 hours using a 20 Amp battery charger.

Similarly it would take approximately 10 hours to charge the battery with a 10 Amp battery charger.

****Please note the figures quoted above could vary depending on the battery condition.***

Dual Chemistry 4 Stage Automatic Battery Chargers

Operating Instructions
Please read these instructions before use



Procedures for Charging a Battery:

The chargers are intended for 12V/24V lead acid and Calcium batteries with a capacity ranging from 50AH to 250AH. DO NOT attempt to recharge non-rechargeable batteries or non lead acid based chemistries.

1. Remove filler caps (for unsealed batteries) from battery and check electrolyte levels in each cell. If the level is low then top up with distilled water.
2. It is recommended to remove the battery from the vehicle or, if this is not practical, then disconnect the leads. If the battery has to remain connected then the battery lead not connected to the chassis has to be connected first. The other connection has to be made to the chassis remote from the battery and fuel line. Ensure that the clips bite firmly and are the correct polarity (+ Pos to + Pos & - Neg to - Neg).
3. Connect the battery charger to the supply mains.
4. Wait a few seconds until the [CHARGE] led starts flashing indicating the battery has been tested and the charge cycle has commenced.
5. If the battery is a Calcium one then press the [MODE] switch and the [CALCIUM] led will turn on indicating the Calcium charge mode.
6. When the charging is completed the [CHARGE] led will stop blinking and you may then disconnect the battery.
7. The batteries can remain connected indefinitely to the charger which will alternate between float and pulse modes for optimum long term battery maintenance.

NOTE: Colour coded clips are as follows : Red for (+) Positive pole and Black for (-) Negative pole.

Specifications		
Model	BC240 - 1230	BC240 - 2418
Input Voltage [VAC]	240 VAC	240 VAC
Input Current [ARMS]	5 ARMS	5.5 ARMS
Bulk Charge Output [VDC±1%] (Pb/Ca)	14.5VDC/15.5VDC	29VDC /31VDC
Float Charge Output [VDC±1%] (Pb/Ca)	13.5VDC /14VDC	27VDC /28VDC
Max Output Current [ADC±5%] (Pb/Ca)	30VDC /28VDC	18VDC /16VDC
Battery Voltage required for start-up	8V	16V
Dimensions [mm] (L x H x W)	250mm X 65mm X 160mm	
Weight [Kg]	2.2Kg	
E.M.I	AS2064 GR.1 A	
Safety Approval	Approval V071019, AS/NZS 3350.2.29	
Protections	Over Temperature, Over Current, Short Circuit, Over Voltage, Reverse Polarity, Bulk Charge Time-Out	
Cooling	Via Fan, Load Activated	
Efficiency (Typical)	Greater than 85%	
Stand By Power	Less than 1W	

Warranty Conditions: The product is warranted to be free from defects in materials and workmanship under normal use and service for a period of 24 months from the date of sale. This warranty covers defective parts and workmanship provided that the product is shipped prepaid to the seller within 24 months of purchase of goods. This warranty is limited to the repair or replacement (at the manufacturers' discretion) of parts and shipping prepaid to the original despatch destination. We regret that no liability can be accepted for consequential or special damages of any kind howsoever arising in connection with products supplied by the seller. This warranty is in lieu of all other warranties expressed or implied. No representative is authorised to assume for the seller any other liability in connection with the seller's products.