

# DC TO AC POWER SOLUTIONS

- Proven Quality • Modern Design • Soft Start • Input to Output Isolation • Portable
- Lightweight • Easy Installation • Reverse Polarity and Output Short Circuit Protection
- Overload and Low Battery Shutdown / Alarm



INV150-12



INV350-12



INV600-12



INV1000-12

Model No.	Rating	Surge	DC Input	GPO's	Wave Form	Efficiency	No Load Alarm/Shutdown	Low Battery Voltage Range	DC Input Size	(L x W x H) (mm)	Weight (Kg)
<b>12V DC Input – 240V AC output</b>											
INV150-12	150W	300W	Cigarette	1	Modified Sine	>85%	300mA	10.5V/10V ±0.5V	10-15.5V	125x102x65	0.9
INV350-12	350W	700W	Alligator Clips	1	Modified Sine	>85%	350mA	10.5V/10V ±0.5V	10-15.5V	180x102x65	1.2
INV600-12	600W	1200W	Alligator Clips	1	Modified Sine	>85%	500mA	10.5V/10V ±0.5V	10-15.5V	245x175x85	2.7
INV1000-12	1000W	2000W	Alligator Clips	2	Modified Sine	>85%	600mA	10.5V/10V ±0.5V	10-15.5V	340x250x90	4.3
INV1500-12	1500W	3000W	Alligator Clips	2	Modified Sine	>85%	700mA	10.5V/10V ±0.5V	10-15.5V	465x250x90	4.6
INV2500-12	2500W	5000W	Alligator Clips	2	Modified Sine	>85%	800mA	10.5V/10V ±0.5V	10-15.5V	480x210x160	10
<b>24 DC Input – 240V AC output</b>											
INV150-24	150W	300W	Cigarette	1	Modified Sine	>85%	300mA	21V/20V ±0.5V	20-30V	125x102x65	0.9
INV350-24	350W	700W	Alligator Clips	1	Modified Sine	>85%	350mA	21V/20V ±0.5V	20-30V	180x102x65	1.2
INV600-24	600W	1200W	Alligator Clips	1	Modified Sine	>85%	400mA	21V/20V ±0.5V	20-30V	245x175x85	2.7
INV1500-24	1500W	3000W	Alligator Clips	2	Modified Sine	>85%	500mA	21V/20V ±0.5V	20-30V	465x250x90	4.6
INV2500-24	2500W	5000W	Alligator Clips	2	Modified Sine	>85%	600mA	21V/20V ±0.5V	20-30V	480x210x160	10
RC1500	Remote Control (On/Off) suits INV1000 & INV1500 Models										
RC2500	Remote Control (On/Off) suits INV2500 Model										